Function and Indicator

① Capslock indicator
② Type-C
③ Toggle switch (left 2.4G wired/ OFF right BT)
④ USB receiver
⑤ Charging indicator
⑥ Multifunctional roller

EN User manual

- Stylish design, 80 key layout, Gasket structure, delicate and soft touch,
- Keycaps and magnetic switches are pluggable. The users can also purchase variousbrands of switches and personalized keycaps on the market for free DIY.
- The keyboard material is solid and the buttons are responsive.
- Two stage tripod with concealed independent storage receiver.
- The user-friendly design of the keyboard, combined with the Fn key, adds a series ofcommonly used shortcut function buttons
- Keyboard return rate: wired mode 8000Hz, 2.4G mode 1000Hz, BT mode 125Hz.

Specifications

- Number of keys: 80 keys
- Product size: 322,7 (L)X143,2 (W) x43,1 (H) +1mm
- Product weight:1172g (including wire/receiver)
- Changing voltage/current DC 5V/1200mA
- Rated voltage: DC 3,7V
- Battery life: about 23 hours (default lighting effect)/about 40 hours (turn off all lights)
- Battery capacity: 4000mAh
- Charging interface: Type-C
- Computer System Requirements:Windows WIN XP, WIN7,WIN8, WIN10(Driver may berequired under Win95 and Win98 systems)

Standard Version Shortcut Key Descriptions

(you have to switch to the corresponding mode FN+~/1/2/3 in the upper left corner to be able to long press on the code)

Fn+	ESC	~	1	2	3
Combined functions	Restore the default	2.4G	BT 1#	BT 2#	BT 3#
Fn+	Q	W	E	|	Wheel button
Combined functions	Android	Windows	Mac	Light effect switching	Light effect switching
Fn+	TAB	↑	↓	←	→
Combined functions	Colour switching	Brightness+	Brightness-	Speed-	Speed+
Fn+	WIN-L	U	I	O	DEL
Combined functions	Lock WIN	PRTSC	SCRLK	PAUSE	INS
Fn+	END	Left shift		|	B
Combined functions	HOME	Light effect of indicator		Light mode switching	Check battery level

FN+Q=Android system (Q button red light flashes for 3s), F area single press function and F area FN combination function.

Key	F1	F2	F3	F4	F5	F6
Single press	Screen Brightness-	Screen Brightness+	conversion window	Return to Desktop	Brightness-	Brightness+
Fn combination	F1	F2	F3	F4	F5	F6
Key	F7	F8	F9	F10	F11	F12
Single press	previous song	Play/Pause	next song	Mute	Volume-	Volume+
Fn combination	F7	F8	F9	F10	F11	F12

FN+W=Windows system (W key red light flashes for 3s), F area single press function and F area FN combination function.

Key	F1	F2	F3	F4	F5	F6
Single press	F1	F2	F3	F4	F5	F6
Fn combination	Home page	Email	conversion window	Open Explorer	Brightness-	Brightness+
Key	F7	F8	F9	F10	F11	F12
Single press	F7	F8	F9	F10	F11	F12
Fn combination	previous	Play/Pause	next song	Mute	Volume-	Volume+

FN+E=Mac system (E button red light flashes for 3s), F zone single press function and F zone FN combination function.

Key	F1	F2	F3	F4	F5	F6
Single press	Screen brightness-	Screen brightness+	conversion window	Return to Desktop	Brightness-	Brightness+
Fn combination	F1	F2	F3	F4	F5	F6
Key	F7	F8	F9	F10	F11	F12
Single press	previous	Play/Pause	next song	Mute	Volume-	Volume+
Fn combination	F7	F8	F9	F10	F11	F12

Operating Instructions

Magnetic Switch Adjustment Method

Equipped with a driver with multiple magnetic switch functions
1.Dynamic Keystroke (DKS): The current button can be modified to bind 1 to 4 functions depending on the degree of pressing and releasing.
2.Press and hold/click (MT) : A single button to achieve two functions; Pressing and holding a button is one type, clicking a button is another type.
3.Switching switch (TGL): It can modify the current button to trigger continuously when clicked, and press and hold the button to trigger normally.
4.SOCD function: SOCD monitors the two selected buttons and activates them according to the settings you have chosen.
5.RS function: Rappy Snappy monitors the two selected keys and activates the deeper pressed key.
6.Quick Trigger Function (RT): Quick Trigger will dynamically adjust your trigger stroke and reset stroke based on your intention to press or release the button.
7.Visualize fast magnetic switch travel calibration.

ИНСТРУКЦИЯ ПО ПРИМЕНЕНИЮ

Пожалуйста, прочитайте инструкцию перед первым использованием.
Спасибо за выбор продуктов AULA.
Компьютерные Клавиатура и мышь – основные устройства управления компьютером, предназначены для ввода данных (могут быть проводными или беспроводными (2.4Гц с передатчиком в комплекте или Bluetooth без передатчика).
Компьютерная гарнитура является устройством ввода/вывода данных, предназначена для ввода данных (голос) посредством микрофона и для вывода данных через наушники. (Могут быть проводными и беспроводными (2.4Гц, Bluetooth, 2.4Гц+ Bluetooth).
Коврик для компьютерной мыши необходим, чтобы обеспечить хорошее сцепление с поверхностью и добиться оптимального скольжения мыши. Коврик устанавливается на поверхности стола, мышь помещается сверху.
Стенд/Подставка для ноутбука/планшета необходима для размещения устройства под удобным углом для работы/игр и дополнительного охлаждения.
Клавиши Z/C/2.3 предназначены для воспроизведения музыки и других аудио файлов, подключается к ПК, ноутбукам, планшетам, смартфонам через разъем 3.5 мм, питается от USB.
USB хаб – это устройство, позволяющее подключить в 1 порт Type-C ряд устройств, таких как: устройства ввода, накопители памяти, дополнительные коннекторы и проводной интернет.
Подробные характеристики товара находятся на сайте www.aulagaming.ru
Подключение:
Аккуратно распакуйте изделие. Разместите на столе, подключите к компьютеру, к свободному порту USB(рекомендуемо) (для гарнитур/ колонок) и проверьте работоспособность.
Импортер: ZHONGXIN SHIN ELECTRONICS CO.,LTD. Адрес: NO.1 HUAYU STREET,CHANGLING VILLAGE HUANGJIANG TOWN,DONGGUAN CITY. Дистрибьютер/импортер: ООО "ЕВРОСТРОЙТОРГ" ЮРИДИЧЕСКИЙ АДРЕС: 109147, МОСКВА, УЛ. ТАГАНСКАЯ, Д.17, КОРП.5, ЭТАЖ 3, ПОМ.VIII, КОМ.1 Производитель: Shenzhen Yuxi Technology Co., Ltd. Адрес производства: 1-3 Building,Jinxiu Road, Pingshan District, Shenzhen, China. Продукция соответствует требованиям ТР ТС 004/2011, ТР ТС 020/2011, ТР ТС 037/2016 Срок службы 2 лет. Изготовлено в соответствии с Техническим регламентом Таможенного союза "О безопасности низкого напряжения" (ТР ТС 004/2011), "Электромагнитная совместимость технических средств" (ТР ТС 020/2011), "Ограничение использования опасных веществ в изделиях электрического и электронного оборудования" (ТР ТС 037/2016). Информация о сертификатах: Декларация соответствия ЕАС. Информация о продукции: Декларация соответствия ЕАС. Информация о производителе: Декларация соответствия ЕАС. Информация о производителе: Декларация соответствия ЕАС. Информация о производителе