正面

AULA

X9

TRI-MODE GAMING MOUSE

FUEL YOUR PASSION

Расположение клавиш продукта



Connection Methods

BT Connection
1.Disconnect the USB cable and turn on the power switch, Slide the mode switch to BT mode. The blue indicator will flash slowly, indicating BT mode.
2.Press and hold the DPI button to enter BT pairing mode, continuously for about 3 seconds, The blue indicator will flash rapidly to enter BT pairing mode.
3.Enable BT on your device and search for available devices. Select "AULA-X9"to connect.
4.When the blue indicator stops flashing and stays solid, the BT connection is successful.
Note: The BT device name may vary depending on the model purchased.

2.4G Wireless Connection
1.Disconnect the USB cable and turn on the power switch.
2.Slide the bottom mode switch to 2.4GHz mode and insert the USB receiver into the computer. The receiver will pair automatically.
Forced Pairing:Press and hold the left, middle, and right buttons simultaneously for 3 seconds.The green indicator willflash, and the receiver indicator will turn off once pairing is completed successfully.

Wired Connection
1.Connect the mouse using the included Type-C USB cable.
2.Plug the other end of the Type-C cable into your device to start using the mouse.

Product Introduction

- Model: X9MAX / X9Ultra
- Product Size: 125 x 63 x 38 mm
- Product Weight: X9MAX: 48 ±1g ,X9Ultra:49 ±1g
- Sensor: PixartPAW3395 Gaming Sensor
- Connection Modes: BT/2.4GHz Wireless/Wired mode
- Battery Capacity:X9MAX/X9Ultra: 500 mAh Lithium Battery
- Input Voltage /Current:DC 5V ⎓ 400mA
- DPI Breathing Indicator(Press the DPI button to cycle DPI levels): X9MAX:800 DPI(Red)/1600 DPI(Green)/2400 DPI(Blue)/3200 DPI (Purple)/6400 DPI (Green)/ 12800 DPI (Red)/26000 DPI (Cyan)
  X9Ultra:400 DPI(Red) /800 DPI(Green) /1200 DPI(Blue) (Default) /1600 DPI (Light Purple) /3200 DPI(Cyan) /4200 DPI(Yellow)
- Charging Interface:USB Type-C
- Polling Rate:125Hz
  Wireless 2.4GHz Mode:8K(125-250-500-1000-8K, software adjustable)
  Wired Mode:8K Hz(125-250-500-1000-8K, software adjustable)
  BT Mode:125Hz
- X9Ultra Polling Rate:
  Wireless 2.4GHz Mode:8K(125-250-500-1000-8K, software adjustable)
  Wired Mode: 8K Hz(125-250-500-1000-8K, software adjustable)
  BT Mode:125Hz

Charging and Battery Indicator

The blue flashing of the red light indicates a low voltage alarm.
The red light stayson during charging and turns off when fully charged.

รูปแบบปุ่มของผลิตภัณฑ์



Please visit the AULA web-based driver to use this product.

The AULA HUB software provides a customizable user experience. Please use the AULA HUB web-based driver to access this feature.

www.aulastar.com

This application is used to perform the following functions:

- Key Assignment
- DPI Adjustment
- Macro Settings
- Polling Rate Settings
- Firmware Upgrade

Precautions

- Please store and use this product under normal ambient temperature conditions.
- Do not use this product near heat sources, such as radiators, heat registers, stoves, or other devices that generate heat.
- Do not drop or throw the product, as impact may cause damage to the device.
- Do not expose the device to dripping or splashing liquids. Do not place objects filled with liquid on the device. If water, beverages, or other liquid or liquid accidentally enters the device, immediately turn off the power and have it inspected by qualified service personnel before further use.
- Regardless of the cause of damage, repairs must be carried out by qualified service personnel in a timely manner. Unauthorized disassembly will void the warranty.
- Do not disassemble, crush, puncture, or dispose of the product in fire. If severe swelling occurs, stop using the product immediately. Do not expose the product to high-temperature environments, and do not use it after immersion in water.
- Product specifications, performance, and functions are subject to change without prior notice.

☆ This product is not sold with a power adapter. If a power adapter is used for power supply, consumers should use a compatible power adapter that has obtained CCC certification and complies with applicable safety standards.

Disposition des touches du produit



Quick Guide to Using 8K Receiver

2.4G Mode:
1. Disconnect the USB cable and turn on the power switch. Slide the switch upward to enter 2.4G wireless mode.
2. Plug in the USB receiver to start using directly.

Forced Pairing:
Press and hold the left, middle, and right buttons simultaneously for 3 seconds, The mouse's green indicator light will flash rapidly. While it's flashing, insert the receiver — once the light turns off, the pairing is complete.

Note:When switching between two receivers, re-pairing is required for proper use.

Розташування клавіш продукту



Product Key Layout



Tata Letak Tombol Produk



제품 키 레이아웃



製品のキーレイアウト



Disposição das Teclas do Produto



產品按鍵佈局



Disposición de Teclas del Producto



Bố trí phím sản phẩm



Produkttastenanordnung



At AULA, passion isn't a feeling - it's our engineering standard. From our industrial roots to the global stage, we obsess over every micron of precision because we know what's at stake. We don't just build gear; we build the bridge between a player's instinct and their ultimate victory. Every click, every win, every heartbeat.

Fuel Your Passion

Disposizione dei Tasti del Prodotto



ИНСТРУКЦИЯ ПО ПРИМЕНЕНИЮ

Пожалуйста, прочитайте инструкцию перед первым использованием.
Спасибо за выбор продукции AULA.
Компьютерные Клавиатура и мышь – основные устройства управления компьютером, предназначены для ввода данных (могут быть проводными или беспроводными (2.4 Гц с передатчиком в комплекте или Bluetooth без передатчика).
Компьютерная гарнитура является устройством ввода/вывода данных, предназначена для ввода данных (голос) посредством микрофона и для вывода данных через наушники. (Могут быть проводными и беспроводными (2.4Гц, Bluetooth, 2.4Гц и Bluetooth).
Коврик для компьютерной мыши необходим, чтобы обеспечить хорошее сцепление поверхностью и добиться оптимального скольжения мыши. Коврик устанавливается на поверхности стола, мышь помещается сверху.
Стенд/Подставка для ноутбука/планшета необходима для размещения устройства под удобным углом для работы/игр и дополнительного охлаждения.
Колонки 2.0/2.1 предназначены для воспроизведения музыки и других аудио файлов, подключаются к ПК, ноутбуку, планшетам, смартфонам через разъем 3.5 мм, питаются от USB.

USB хаб - это устройство, позволяющее подключить в 1 порт Type-C ряд устройств, таких как: устройства ввода, накопители памяти, дополнительные мониторы и проводной интернет.
Подробные характеристики товара находятся на сайте www.aulagaming.ru

Подключение:
Аккуратно распакуйте изделие. Разместите на столе, подключите к компьютеру, к свободному порту USB(аудиоразъему (для гарнитуры/ колонки) и проверьте работоспособность.

Изготовитель: DONGGUAN SUOXI ELECTRONICS CO., LTD. Адрес: NO.1 HUANYI STREET,1 HUANGCHENG VILLAGE HONGCHANG TOWN,DONGGUAN CITY,GUANGDONG PROVINCE,CHINA. Продукция соответствует требованиям ТР ТС 020/2011 «Электромагнитная совместимость технических средств», ТР ТС 004/2011 «О безопасности низковольтного оборудования», ТР ТС 037/2016 «Об ограничении применения опасных веществ в изделиях электрического и электронного оборудования», ТР ТС 017/2011 «О безопасности продукции легкой промышленности», ТР ТС 007/2011 «О безопасности детей», ТР ТС 021/2011 «О безопасности пищевой продукции», ТР ТС 005/2011 «О безопасности упаковки», Bluetooth, 2.4Гц, Type-C, Bluetooth, 2.4Гц и Bluetooth. Гарантийный срок: 1 год. Срок службы: 2 года. Гарантийные обязательства будут приняты к рассмотрению при наличии: 1. Гарантийного талона. 2. Кассового чека. Не ремонтируются: 1. Изделия, в которых обнаружены следы самостоятельного ремонта. 2. Изделия, в которых обнаружены следы воздействия жидкости. 3. Изделия, в которых обнаружены следы механического воздействия