正面

AULA

Kunlun X5

TRIMODE GAMING MOUSE

FUEL YOUR PASSION

Расположение клавиш продукта



Product Specifications

- Mouse dimensions: 125.37 (L) × 63.23 (W) × 39.86 (H) +0.1mm
- Product weight: Approx. 69g (excluding receiver)
- Connectivity: BT / 2.4G / Wired modes
- Polling Rate: Up to 8000Hz
- Operating voltage (2.4G wireless mode): DC 3.7V (built-in Li-ion battery, max 4.2V when fully charged)
- Operating voltage (wired mode): 5V ±5%
- Charging voltage/current: DC 5V ⎓ 300mA
- Battery capacity (wireless): Approx. 15mA (at 8K polling rate) / Approx. 6mA (at 1K polling rate)
- Charging port: USB-C
- Battery life: Approx. 38.5 hours (at 8K polling rate) / 83 hours (at 1K polling rate)
- BT device name: AULA-X5 Ultra-1/2

Low-voltage warning:

The mouse indicator flashes red slowly 20 times to alert the user to charge the battery.

Connection Methods

BT Connection

1.Switch the bottom switch to BT mode, then press and hold the DPI button for 3 seconds to enter pairing mode (broadcasting will start automatically if no Bluetooth connection). The DPI indicator flashes blue a solid blue light for about 2 seconds indicates successful pairing.

2.To switch to BT channel 2, press and hold the middle button and the back button simultaneously for 5 seconds. The indicator will flash cyan; a solid cyan light for about 2 seconds confirms successful pairing. The pairing process automatically times out.

3.To return from BT channel 2 to channel 1, press and hold the middle button and the forward button for 5 seconds. Once the BT device is deleted from the host, it will not automatically reconnect; you must re-pair it.

2.4G Wireless Connection

1.For 2.4G mode, you can click the "Pair" button in the driver to enter pairing mode, then press and hold the DPI button for 3 seconds. The mouse's green LED will flash. Insert the receiver after that. When pairing is successful, the green LED turns off. The pairing distance should be ≤10 meters.

2.Pairing can also be performed directly within the driver. The mouse is pre-paired by default from the factory and is ready to use out of the box. It comes with a high-speed, strong anti-interference Mini receiver that supports an 8K polling rate – plug and play.

Wired Connection

1.Connect the Type-C cable and the device is ready for immediate use.

รูปแบบปุ่มของผลิตภัณฑ์



Please visit the AULA web-based driver to use this product.

The AULA HUB software provides a customizable user experience. Please use the AULA HUB web-based driver to access this feature.

www.aulastar.com

This application is used to perform the following functions:

- Rapid Trigger Adjustment
- DPI Adjustment
- Macro Settings
- Polling Rate Settings
- Firmware Upgrade
- Key Assignment
- Actuation Point Settings
- Click Actuation Feedback Settings

Product Introduction

- 5 adjustable DPI levels with independent DPI indicator: 400 (Red) / 800 (Green) / 1600 (Blue) / 3200 (Yellow) / 6400 (Purple) / 7200 (Cyan) / 16000 (Yellow). Up to 50000 DPI can be set via the driver.
- Driver with RGB palette: The indicator light can be customized to over 16 million colors.
- 7 adjustable polling rates: 125 / 250 / 500 / 1000 / 2000 / 4000 / 8000 Hz
- DPI range: 400 – 800 – 1600 – 3200 – 50000 – 56000 (adjustable)
- Ergonomic design: Provides a comfortable grip and reduces hand fatigue during extended use.
- Built-in OTP over-temperature protection and 500mAh high-capacity battery: Ensures reliable, long-lasting performance with enhanced safety.
- High-end PAW3950 power-efficient sensor: Delivers smooth, precise cursor tracking with fine movement resolution.
- The mouse is equipped with the Starlink Stepping Haptic System (Left/Right Actuation Feedback): Provides tactile feedback upon actuation of the left and right button actuation travel with 10 trigger points.
- Rapid Trigger (RT) function: Provides faster shooting response in FPS games.
- Haptic feedback: 5 adjustable levels, ranging from light to strong, to enhance the gaming experience.
- Calibration and travel visualization: Calibration requires pressing the button fully for one second after clicking "Calibrate" in the driver. The system will indicate when calibration is complete, ensuring precise SOHS performance and an optimized user experience.

Disposition des touches du produit



Quick Guide to Using 8K Receiver

2.4G Mode:
1.Disconnect the USB cable and turn on the power switch. Slide the switch downward to enter 2.4G wireless mode.
2.Insert the USB receiver and start using it immediately.

Forced pairing:
Press and hold the DPI button for approximately 3 seconds. The green indicator will blink quickly. During the blinking, insert the USB receiver → the pairing finishes when the indicator light goes out.

Receiver Adapter:
The included receiver adapter extends the dongle from your case to the desktop, reducing distance for rock-solid wireless stability and ultra-low latency – no more stutter, no more lag.

Розташування клавіш продукту



Product Key Layout



Tata Letak Tombol Produk



제품 키 레이아웃



製品のキーレイアウト



Disposição das Teclas do Produto



產品按鍵佈局



Disposición de Teclas del Producto



Bố trí phím sản phẩm



Produkttastenanordnung



AULA

At AULA, passion isn't a feeling - it's our engineering standard. From our industrial roots to the global stage, we obsess over every micron of precision because we know what's at stake. We don't just build gear; we build the bridge between a player's instinct and their ultimate victory. Every click, every win, every heartbeat.

Fuel Your Passion

Disposizione dei Tasti del Prodotto



ИНСТРУКЦИЯ ПО ПРИМЕНЕНИЮ

Покупатель, прочитайте инструкцию перед первым использованием.
Спасибо за выбор продуктов AULA.

Компьютерные Клавиатура и мышь – основные устройства управления компьютером, предназначены для ввода данных (могут быть проводными или беспроводными (2.4 Гц с передатчиком и комплект или Bluetooth без передатчика).

Беспроводные адаптеры являются устройствами ввода/вывода данных, предназначены для ввода данных (клавиш) передаётся микроволны и для вывода данных через наушники. (могут быть проводными и беспроводными (2.4Hz, Bluetooth, 2.4Gz+ Bluetooth).

Коврик для компьютерной мыши необходим, чтобы обеспечить хорошее сцепление с поверхностью и добиться оптимального скольжения мыши. Коврик устанавливается на поверхности стола, мышь помещается сверху.

Стенд/Подставка для наушниковхолдера необходима для размещения устройства под удобным углом для работы/игр и дополнительного охлаждения.

Колонка 2.0/2.1 предназначены для воспроизведения музыки и других аудио файлов, подключаются к ПК, ноутбукам, планшетам, смартфонам через разъем 3.5 мм, питаются от USB.

USB хаб - это устройство, позволяющее подключить к 1 порту Type-C ряд устройств, таких как: устройство ввода, накопители памяти, дополнительные мониторы и проводной интернет.

Подробные характеристики товара находятся на сайте www.aulagaming.ru

Предупреждение:
Аккуратно распакуйте изделие. Разместите на столе, подключите к компьютеру, а свободную порту USB одновременно (для принтера/ колонки) и проверьте работоспособность.

Внимание: ЗАПРЕЩАЕТСЯ ОТКРЫВАТЬ, ПЕРЕДЕЛАТЬ, ВНОСИТЬ ЛЮБЫЕ ИЗМЕНЕНИЯ ПОВРЕЖДЕНИЯ ПОЖАЛОВАТЬ ГАРАНТИЙНЫЙ ТАЛОН. Не допускайте попадания на изделие влаги, пыли, агрессивных химических веществ и прочих жидкостей. Не подвергать к ударам, сдавливанию, вибрации, нагреванию, замерзанию. Не подвергать к воздействию прямых лучей солнца. Не подвергать к воздействию высокого напряжения. Не пытаться разобрать изделие самостоятельно. Не пытаться ремонтировать изделие самостоятельно. Не пользоваться в помещениях с температурой ниже 0 и выше +40 С. Не пользоваться при повышенной влажности. Не пользоваться при сильной запылённости. Не пользоваться при сильных электромагнитных полях. Не пользоваться при сильных радиопомехах. Не пользоваться при сильных вибрациях. Не пользоваться при сильных ударах. Не пользоваться при сильном нагреве. Не пользоваться при сильном охлаждении. Не пользоваться при сильном ветре. Не пользоваться при сильном дождем. Не пользоваться при сильном снегопаде. Не пользоваться при сильном тумане. Не пользоваться при сильном дыме. Не пользоваться при сильном запахе. Не пользоваться при сильном шуме. Не пользоваться при сильном свете